

Moxi™ 20

312 BTE canal receiver technology (CRT)

Signature features

20 channels

Next generation automatic with SmartFocus

Clients can experience superior automatic performance with the optimal blend of 3 listening environments plus a unique specialized treatment of music. In addition, the integration of SmartFocus™ further improves speech understanding in noise or provides optimal comfort automatically

Natural Sound Balance

An adaptive feature to minimize artifacts that can occur when amplified sound combines in the ear canal with direct sound. Natural Sound Balance continuously monitors these sounds and makes precision adjustments to preserve a clear, balanced signal

Pinna Effect

This feature uses sophisticated calculations to recreate natural directionality

Next generation feedback manager

Harnessing the power of Unitron's new Era™ platform, the next generation feedback manager offers maximum usable gain by suppressing feedback transients before they become audible

Self learning

Capable of learning client preferences for SmartFocus and volume control in all programs. Clients are able to accelerate the learning by using the LearnNow feature

Wireless technology

Binaural Phone – streams audio to the non-phone ear, allowing for binaural hearing while using a phone

DuoLink – program, volume and SmartFocus adjustments conducted on one hearing instrument are automatically transferred to the other ear

uDirect™ (optional) – interface between wireless hearing instruments and Bluetooth-enabled devices, such as cell phones, and stereo streaming to the hearing instrument from devices such as MP3 players or uTV™

uTV (optional) – streams audio from a TV or audio source to the uDirect


Smart Control (optional)

Remote control provides access to an array of adjustable parameters


Additional features

- Multiband adaptive directional microphone
- Telecoil
- 3 manual + 3 wireless streaming programs
- AntiShock™
- MyMusic™
- Wind noise manager
- Speech enhancement LD
- Noise reduction
- Data logging
- Easy-t
- Optional wireless programming with iCube


Fitting guides



Moxi 20 (xS)








Moxi 20 power (xP)







Moxi 20 super power (xSP)

Moxi 20 is suitable for fitting mild to severe hearing losses and can fit audiogram configurations ranging from reverse to precipitously sloping.

ANSI 3.22 2003/IEC 118-7 2CC COUPLER TECHNICAL DATA

| | Moxi 20 standard (xS receiver) | Moxi 20 power (xP receiver) | Moxi 20 super power (xSP receiver) |
|--|--------------------------------|-----------------------------|------------------------------------|
| Reference test frequency - IEC 118-7 (kHz) | 1.6 | 1.6 | 1.6 |
|  OSPL₉₀ | | | |
| Maximum (dB SPL) | 112 | 126 | 129 |
| Nominal (dB SPL) | 109 | 123 | 126 |
| ANSI HFA (dB SPL) | 105 | 118 | 120 |
| at RTF (dB SPL) | 104 | 120 | 124 |
|  Full on gain (input 50 dB SPL) | | | |
| Maximum (dB) | 45 | 55 | 61 |
| ANSI HFA (dB) | 39 | 48 | 55 |
| at RTF (dB) | 38 | 49 | 60 |
|  Basic frequency response (ANSI 2003) | | | |
| Frequency range (Hz) | <100-8300 | <100-7300 | <100-5500 |
| HFA reference test gain (dB) | 28 | 41 | 43 |
| Current drain at RTG (mA) | 1.15 | 1.25 | 1.2 |
| Typical battery life (h) | 141 | 130 | 135 |
| Equivalent input noise at RTG (dB SPL) | 19 | 18 | 19 |
| Total harmonic distortion at 500 Hz/800 Hz/1600 Hz (%) | 1.0/1.0/1.0 | 1.5/1.0/0.5 | 0.5/0.5/0.5 |
|  Induction coil sensitivity (ANSI 2003, 31.6 mA/m) | | | |
| HFA SPLITS/STS-RSETS (dB SPL/dB) | 88/0 | 101/0 | 103/0 |
| EMC immunity by ANSI c63.19-2001 EMC, omni/telecoil | M4/T4 | M4/T4 | M4/T4 |
|  Moxi xSP: mic at 70 dB SPL vs induction coil at 100 mA/m | | | |

IEC 118-0 OES COUPLER TECHNICAL DATA

| | Moxi 20 standard (xS receiver) | Moxi 20 power (xP receiver) | Moxi 20 super power (xSP receiver) |
|--|--------------------------------|-----------------------------|------------------------------------|
| Reference test frequency - IEC 118-0 (kHz) | 1.6 | 1.6 | 1.6 |
|  OSPL₉₀ | | | |
| Maximum (dB SPL) | 121 | 132 | 133 |
| at RTF (dB SPL) | 113 | 129 | 132 |
|  Full on gain (input 50 dB SPL) | | | |
| Maximum (dB) | 56 | 65 | 69 |
| at RTF (dB) | 46 | 58 | 68 |
|  Basic frequency response | | | |
| Frequency range (DIN 45605) (Hz) | <100-8600 | <100-7500 | <100-5800 |
| Reference test gain (dB) | 39 | 51 | 57 |
| Current drain at RTG (mA) | 1.15 | 1.2 | 1.2 |
| Typical battery life (h) | 141 | 135 | 135 |
| Equivalent input noise at RTG (dB SPL) | 19 | 18 | 19 |
| Total harmonic distortion at 500 Hz/800 Hz/1600 Hz (%) | 1.0/1.5/1.5 | 1.5/1.5/1.0 | 1.0/1.0/0.5 |
|  Induction coil sensitivity | | | |
| at RTF (graph shown for 31.6 mA/m at RTG) (dB SPL) | 99 | 109 | 117 |
| EMC immunity by IEC 60118-13, field strength 75/50 V/m, omni IRIL low/high band (dB SPL) | 42/46 | 42/46 | 42/46 |

- Legend**
- Moxi 20 xS
 - Moxi 20 xP
 - Moxi 20 xSP

TEST CONDITIONS

Battery size: 312; Source: voltage 1.3 V;
 The measurements obtained with a closed configuration using an HA-1 coupler (ANSI-3.7-1995) or occluded ear simulator (EN 60711, coupling arrangement according to fig. 4 in the test standard). The hearing instrument set to linear, omni mode with all adaptive features disabled.
 Domes should never be fit on patients with perforated eardrums, exposed middle ear cavities, or surgically altered ear canals.
 In the case of such a condition, we recommend use of a customized earmold.
 Sound pressure level of these hearing aids exceeds 132 dB SPL.
 We reserve the right to change specification data without notice as improvements are introduced.